

Life is on

At Phonak, we believe that well-hearing equates to well-being and is essential to living life to the fullest. For more than 70 years, we have remained passionate about creating a world where 'life is on' for everyone. Our innovative hearing solutions are designed for people of all ages and all degrees of hearing loss, to connect socially, thrive mentally and emotionally.

www.phonakpro.com/rogerfocus

Roger Focus II



Focus on what matters

For more information visit www.phonakpro.com/rogerfocus

027-0601-02/V1.00/2020-04/na © 2020 Sonova AG All rights reserved

Product description

			
		Roger Focus II-312	Roger Focus II
Battery type		312	built-in rechargeable
Multi-function button		•	•
Multi-function button volume adjustment		-8 dB <-> +8 dB (2 dB step)	-8 dB <-> +8 dB (2 dB step)
Indicator light		•	•
Colors		2	10
Nano coating		•	•
IP rating		IP68*	IP68*
Dimensions	L x W x D	31.3 x 14.1 x 7.3 (1.23 x 0.56 x 0.29")	36.7 x 16.4 x 8.5 (1.44 x 0.65 x 0.33")
	Weight	2.18 g / 0.077 oz	3.71 g / 0.131 oz
Charging times	0% to 100%		3 h
	0% to 80%		1.5 h
		SlimTube HE	SlimTube HE
Max. Power Output		90 dBA freefield equivalent	90 dBA freefield equivalent
Frequency range (Hz)		<100 - >7000	<100 - >7000
Working current (mA)		1.5	1.5
Roger characteristics			
Frequency			
Antenna		2.4 GHz including adaptive automatic frequency hopping	
Backlink RF power		built-in antenna	
		< 0.02 mW	

* IP68 indicates that the hearing aid is water resistant and dust tight. It survived continuous immersion in 1 meter of water for 60 minutes and 8 hours in a dust chamber as per the IEC60529 standard.

Housing colors

Roger Focus II



Roger Focus II-312



Acoustic coupling

Sound outlet	SlimTube HE	Available in left, right and five different lengths (00, 0, 1, 2, 3)
Earpiece for SlimTube	Dome	Open dome, available in three sizes (S, M, L)

Wireless communication portfolio

Roger™	Roger Focus II-312	Roger Focus II
Roger™ microphones	•	•

Fitting

Roger Focus II is solely a Roger receiver. No fitting required.

Phonak Charger BTE RIC

This charger is suitable for Roger Focus II. It features a USB-C charging inlet, an indicator light and a holding space for SlimTube.



Phonak RemoteControl

The Phonak RemoteControl is suitable for Roger Focus II. It allows volume adjustments and locks the volume button.

